


TAO 1pro



User Manual



Content

Declarations	3
FCC/Warranty	3
Operators Safety Summary	4
Installation Safety Summary	4
Chapter 1 Your Product	5
1.1 In the Box	5
1.2 Product Overview	6
SYSTEM CONNECTION	6
1.2.1 Key Feature	6
1.2.2 Front Panel	7
1.2.3 Interface Panel	8
1.3 Dimension	9
Chapter 2 Install Your Product	10
2.1 Plug in Power	10
2.2 Turn on Your TAO 1pro	10
2.3 Connecting Input Signal Source	10
2.4 Connecting HDMI Output	11
2.5 Connecting Network	11
2.6 Connecting Microphone and External Monitoring Devices	11
Chapter 3 Use Your Product	12
3.1 Menu	12
3.2 Signal Switching	16
3.3 Streaming	17
3.4 Record	18
3.5 Audio Column	19
3.6 Rotation	20
3.7 Lock Screen and Power Off	21
3.8 Battery Installation	21
3.9 Upgrade	23
Chapter 4 Ordering Codes	24
4.1 Product	24
Chapter 5 Support	25
5.1 Contact us	25
Chapter 6 Appendix	26
6.1 Specification	26
6.2 Terms & Definitions	27
6.3 Revision History	33

Thank you for choosing our product!

This User Manual is designed to show you how to use this video processor quickly and make use of all the features. Please read all directions and instructions carefully before using this product.

Declarations

FCC/Warranty

Federal Communications Commission (FCC) Statement

This equipment has been tested and found to comply with the limits for a class A digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area may cause harmful interference, in which case the user will be responsible for correcting any interference.

Guarantee and Compensation

RGBlink provides a guarantee relating to perfect manufacturing as part of the legally stipulated terms of guarantee. On receipt, the purchaser must immediately inspect all delivered goods for damage incurred during transport, as well as for material and manufacturing faults. RGBlink must be informed immediately in writing of any complains.

The period of guarantee begins on the date of transfer of risks, in the case of special systems and software on the date of commissioning, at latest 30 days after the transfer of risks. In the event of justified notice of compliant, RGBlink can repair the fault or provide a replacement at its own discretion within an appropriate period. If this measure proves to be impossible or unsuccessful, the purchaser can demand a reduction in the purchase price or cancellation of the contract. All other claims, in particular those relating to compensation for direct or indirect damage, and also damage attributed to the operation of software as well as to other service provided by RGBlink, being a component of the system or independent service, will be deemed invalid provided the damage is not proven to be attributed to the absence of properties guaranteed in writing or due to the intent or gross negligence or part of RGBlink.

If the purchaser or a third party carries out modifications or repairs on goods delivered by RGBlink, or if the goods are handled incorrectly, in particular if the systems are commissioned operated incorrectly or if, after the transfer of risks, the goods are subject to influences not agreed upon in the contract, all guarantee claims of the purchaser will be rendered invalid. Not included in the guarantee coverage are system failures which are attributed to programs or special electronic circuitry provided by the purchaser, e.g. interfaces. Normal wear as well as normal maintenance are not subject to the guarantee provided by RGBlink either.

The environmental conditions as well as the servicing and maintenance regulations specified in this manual must be complied with by the customer.

Operators Safety Summary

The general safety information in this summary is for operating personnel.

Do Not Remove Covers or Panels

There are no user-serviceable parts within the unit. Removal of the top cover will expose dangerous voltages. To avoid personal injury, do not remove the top cover. Do not operate the unit without the cover installed.

Power Source

This product is intended to operate from a power source that will not apply more than 230 volts rms between the supply conductors or between both supply conductor and ground. A protective ground connection by way of grounding conductor in the power cord is essential for safe operation.

Do Not Operate in Explosive Atmospheres

To avoid explosion, do not operate this product in an explosive atmosphere.

Installation Safety Summary

Safety Precautions

For all product installation procedures, please observe the following important safety and handling rules to avoid damage to yourself and the equipment.

To protect users from electric shock, ensure that the chassis connects to earth via the ground wire provided in the AC power Cord.

The AC Socket-outlet should be installed near the equipment and be easily accessible.

Unpacking and Inspection

Before opening product shipping box, inspect it for damage. If you find any damage, notify the shipping carrier immediately for all claims adjustments. As you open the box, compare its contents against the packing slip. If you find any shortages, contact your sales representative.

Once you have removed all the components from their packaging and checked that all the listed components are present, visually inspect the system to ensure there was no damage during shipping. If there is damage, notify the shipping carrier immediately for all claims adjustments.

Site Preparation

The environment in which you install your product should be clean, properly lit, free from static, and have adequate power, ventilation, and space for all components.

Chapter 1 Your Product

1.1 In the Box

Power Adapter



Type-C Power Cord



Doublethread

1/4 Screw




1.2 Product Overview

TAO 1pro is a new generation of portable product developed by RGBlink for live streaming.

TAO 1pro has two USB 3.0 inputs connecting with cameras, one HDMI 2.0 input supporting up to 4K@60, one HDMI loop out and one HDMI 1.3 output; Besides, audio input supports MIC and Line input, audio delay and audio mixing are also added; TAO 1pro also supports touching control on the 5.5 inch screen supporting up to 1920*1080 resolution.

Meanwhile, TAO 1pro also supports remote control via dedicated apps on Window/Mac PC and iOS/ Android phone. TAO 1pro integrates signal acquisition, signal monitoring, output expansion and live streaming into one. Multi-functions and exquisite outlook can help you achieve various scenario applications.




SYSTEM CONNECTION

1.2.1 Key Feature


- 5.5 inch HD touch screen for operation
- Network HD streaming
- Asynchronous rotation of main screen and HDMI output
- 2*UVC inputs, 1*HDMI input and 1* HDMI loop
- Audio mixing and latency
- Preview multi-inputs
- Image and color correction
- Recording via USB 2.0 port, SD card stores up to 2T
- Powered via Type C(PD3.0 protocol) and battery(dual backup)

1.2.2 Front Panel



No.	Item	Description
1	Power Button	long press 3 seconds to turn on/off the device
2	Touch Screen	5.5 inch touch screen for menu control

1.2.3 Interface Panel




No.	Connectors	Number	Description
1	HDMI IN/LOOP	1×HDMI IN/ LOOP	Connect to camera and computer
2	HDMI OUT	1×HDMI OUT	Connctet to monitor to view the image
3	Type C	1×PD Type C	Connect to the power supply
4	Audio	1×AUDIO IN/OUT	Connect to microphone and earphone
5	LAN	1×RJ45	Output rate up to 100Mbit/s
6	USB 2.0	1×USB Type A	Connect to harddisk for recording,and storage up to 2T
7	SD slot	1×SD slot	Connect SD card for upgrading,and storage up to 64G
8	USB 3.0	2×USB Type A	Connect to USB camera for UVC capture

1.3 Dimension

Following is the dimension of TAO 1pro for your reference:

161mm×106mm×28mm



Chapter 2 Install Your Product

2.1 Plug in Power

RGBlink TAO 1pro is packaged with a Type C power link cable and a standard power adapter. When linking the power supply, please check the power supply standard used in your country/region.

Besides,TAO 1pro also supports power supply via batteries.(Battery options in 3.8 for your reference)



2.2 Turn on Your TAO 1pro

After TAO 1pro is connected to power supply, long press the Power button 3 seconds on the top panel,the device will enter to the boot interface and enter operation interface.



2.3 Connecting Input Signal Source

You can use any camera, computer or other HDMI/USB 3.0 device as the input source of the TAO 1pro. You can see the resolution of the input signal on the 5.5 inch touch screen when there is active signal plug in.



2.4 Connecting HDMI Output

You can use an HDMI cable to connect the HDMI output to a monitor with an HDMI input interface, so that you can monitor the input, output and audio display in real time.



2.5 Connecting Network

On the left panel of TAO 1pro, there is a LAN port which can be connected to the router via CAT6 cable for live streaming. (Details refers to 3.5)



2.6 Connecting Microphone and External Monitoring Devices

On the left panel of TAO 1pro, there are two 3.5mm standard interfaces which can be directly connected to the microphone or wireless MIC. You can also use external speakers or headphones to monitor the main output audio signal in real time. Audio supports 0~60DB.



Chapter 3 Use Your Product

3.1 Menu

There is a 5.5 inch touch screen on TAO 1pro front board, whose resolution is up to 1920*1080. Most operation can be done on the screen, so let's see this touch screen first.

Input

You can view the inputs, resolution and record files on the top left corner;


Gently touch and open 【Input】 menu to switch USB/HDMI inputs and select the input format.

If you would like to quickly switch the input signal, then touch the <HDMI> in top left corner to switch among UVC1, UVC2 and HDMI.




Record File

Gently touch and open 【Record File】 menu to view the record information.



Batteries

Gently touch and open 【Batteries】 menu to view the battery capacity.



Bottom Menu

You can see the buttons of audio bar,volume adjust,Rec,play,Menu,Shortcut menu and Stream Settings.



Shortcut Menu

Mode Select

In the menu,you can select Display Scale:Auto/16:9/16:10/4:3;

Besides,TAO 1pro supports Crop,Deformation Mode,Horizontal Mirroring,Vertical Mirroring and PIP.



Graph Parameters

In the menu, you can turn ON/OFF HDR.

Color Temperature, Backlight, Brightness, Contrast and Saturation can be adjusted in the menu.



Image Parameter

In the menu, you can view Oscillograph, Vectorgraph, Luminance Histogram, Audio Column and Single Color. Single Color options: grey, red, green and blue.



Settings


In the menu,inputs,outputs,OSD,mirroring,rotate and SD card,fan and language can be set according to your need.



3.2 Signal Switching


TAO 1pro supports signal switching in whether in preview,record or live streaming.

Gently touch 【HDMI】 in the top left menu,signal seamless switching can be achieved.




3.3 Streaming


1.Connect TAO 1pro LAN port to the network first,touch 【Stream Settings】 ,and Streaming Address from third party has been imported via U disk.



2.Before turn ON Streaming Switch,set resolution,streaming mode and code rate first.




3.4 Record


1. Plug harddisk to TAO 1pro USB 2.0 port(supported record format is MP4)
2. Click the button  in the bottom menu can start/pause record.(every record files supports up to 8G)



3. Gently touch 【Menu】 to open 【Record Settings】,you can set record file name,date and time.



4. Open 【File Naming】 menu,customize the name and click Save.



3. Open 【Date&Time】 menu,date and time can be adjust via "+" and "-" icon.




3.5 Audio Columnn

Gently touch audio column in the lower left corner to open 【Audio】 menu. There are three audio columns in the interface, one HDMI 2.0 input audio, one 3.5 mm analog audio input and one 3.5mm analog audio output. Every audio column is divided into left/right channel. You can select one output from two audio inputs and adjust the volume to make the effect better.



3.6 Rotation

TAO 1pro supports rotation setting.


Gently touch the icon  to open 【Settings】 menu, and turn ON 【Rotation Settings】, the output image will rotate as shown below.



3.7 Lock Screen and Power Off

Lock Screen: touch 【Menu】 to open 【Record Settings】, select 【Lock Screen】;

Power Off: 1. Long press 【Power Off】 3 seconds; 2. Long press power button on the top panel.



3.8 Battery Installation

TAO 1pro supports power supply via Type C cable as well as two batteries.

Install: put the batteries into the slots until it is locked in the correct position.

Remove: press lock button at the bottom of the battery to remove it.



Following is batteries options for your reference.

No.	Image	Model	Capacity	Weight	Working hours
1		NEEWER 970	6600mA	600g	4~5 hours
2		Sony NP-F970	6600mA	300g	4~5 hours
3		Sony NP-F550	1500mA	95g	1 hour
4		Sony NP-F750	3000mA	200g	2 hours
5		Sony NP-F570	2200mA	About 100g	1.5 hours
6		Sony NP-F770	4400mA	About 200g	3 hours
7		Sony NP-F960	5400mA	300g	3~4 hours

3.9 Upgrade

Tool: U disk(including the latest firmware)

Upgrade:

1. Power on the device and plug U disk to the USB 2.0 interface;
2. During the upgrade process,the screen on TAO 1pro will turn grey and the device will automatically power-off after upgrading.
3. TAO 1pro will now upgraded while restarting.

Chapter 4 Ordering Codes

4.1 Product


410-5513-01-0

TAO 1pro

Chapter 5 Support

5.1 Contact us

www.rgblink.com



Inquiries

+86-592-577-1197

info@rgblink.com

rgblink.com/contact-us

Global Support

support@rgblink.com

rgblink.com/support-me



@RGLINK



/rgblink



+rgblink



/rgblink



rgblink



rgblink

RGblink Headquarters Xiamen, China

6th Floor Weiye Building
Torch Park Hi Tech Zone
Huli

sales@rgblink.com

+86-592-577-1197

China Regional Sales & Support Shenzhen, China

11th Floor Baiwang Building
5318 Shahe West Road
Baimang, Nanshan

+86-755-2153-5149

Beijing Region Office Beijing, China

Building 8, 25 Qixiao Road
Shahe Town Changping

+86-4008-592-114

Europe Regional Sales & Support Eindhoven, Holland

Flight Forum Eindhoven
5657 DW

eu@rgblink.com

+31(040)-202-71-83

India Regional Sales & Support Mumbai, India

78/626, Motilal Nagar, No1,
Rd No1, Goregaon West,
Mumbai

support@rgblink.com

+91-98200-86718

Chapter 6 Appendix

6.1 Specification

Connectors	Input	HDMI 2.0	2×HDMI-A (1 In 1 Loop)
		USB 3.0	2×USB TypeA
	Output	HDMI 1.3	1×HDMI-A
	Record	USB 2.0	1×USB TypeA
		SD slot	1×SD slot
	Audio	In	1×3.5mm audio jack
		Out	1×3.5mm audio jack
Performance	Control/Stream	LAN	1×RJ45
	Power		1×PD Type-C
	Input Resolution	HDMI	
		SMPTE	720p@50/60 1080i@50 1080p@23/24/30/50/60 1440p@60 2160p@60
		VESA	1024×768@60 1280×720@60 1280×768@60 1280×800@60 1280×1024@60 1360×768@60 1366×768@60 1440×900@60 1600×1200@60 1680×1050@60 1920×1080@60 3840×2160@60
	Output Resolution	HDMI	
		SMPTE	720p@50/60 1080p@24/25/30/50/60
		VESA	1024×768@60 1280×720@50/60 1280×768@60 1280×1024@60 1360×768@60 1920×1080@24/25/30/50/60
Power	Supported	HDMI	2.0
	Standard	USB	3.0
Environment	Input Voltage	12V /1.5A	
	Max Power	16W	
Physical	Temperature	0°C~55°C	
	Humidity	5%~85%	
Physical	Weight	Net	0.88kg
		Package	1.25kg

	Dimension	Net	161mm×106mm×28mm
		Package	255mm×145mm×85mm

6.2 Terms & Definitions

● **RCA:** Connector used primarily in consumer AV equipment for both audio and video. The RCA connector was developed by the Radio Corporation of America.

● **BNC:** Stands for Bayonet Neill-Concelman. A cable connector used extensively in television (named for its inventors). A cylindrical bayonet connector that operates with a twist-locking motion .

● **CVBS:** CVBS or Composite video, is an analog video signal without audio. Most commonly CVBS is used for transmission of standard definition signals. In consumer applications the connector is typically RCA type, while in professional applications the connector is BNC type.

● **YPbPr:** Used to describe the colour space for progressive-scan. Otherwise known as component video.

● **VGA:** Video Graphics Array. VGA is an analog signal typically used on earlier computers. The signal is non-interlaced in modes 1, 2, and 3 and interlaced when using in mode.

● **DVI:** Digital Visual Interface. The digital video connectivity standard that was developed by DDWG (Digital Display Work Group). This connection standard offers two different connectors: one with 24 pins that handles digital video signals only, and one with 29 pins that handles both digital and analog video.

● **SDI:** Serial Digital Interface. Standard definition video is carried on this 270 Mbps data transfer rate. Video pixels are characterized with a 10-bit depth and 4:2:2 color quantization. Ancillary data is included on this interface and typically includes audio or other metadata. Up to sixteen audio channels can be transmitted. Audio is organised into blocks of 4 stereo pairs. Connector is BNC.

● **HD-SDI:** High-definition serial digital interface (HD-SDI), is standardized in SMPTE 292M this provides a nominal data rate of 1.485 Gbit/s.

● **3G-SDI:** Standardized in SMPTE 424M, consists of a single 2.970 Gbit/s serial link that allows replacing dual link HD-SDI.

● **6G-SDI:** Standardized in SMPTE ST-2081 released in 2015, 6Gbit/s bitrate and able to support 2160p@30.

● **12G-SDI:** Standardized in SMPTE ST-2082 released in 2015, 12Gbit/s bitrate and able to support 2160p@60.

● **U-SDI:** Technology for transmitting large-volume 8K signals over a single cable. a signal interface called the ultra high definition signal/data interface (U-SDI) for transmitting 4K and 8K signals using a single optical cable. The interface was standardized as the SMPTE ST 2036-4.

● **HDMI:** High Definition Multimedia Interface: An interface used for the transmission of uncompressed high definition video, up to 8 channels of audio, and control signals, over a single cable.

● **HDMI 1.3:** Released on June 22 2006, and increased the maximum TMDS clock to 340 MHz (10.2 Gbit/s). Support resolution 1920 × 1080 at 120 Hz or 2560 × 1440 at 60 Hz). It added support for 10 bpc, 12 bpc, and 16 bpc color depth (30, 36, and 48 bit/px), called deep color.

● **HDMI 1.4:** Released on June 5, 2009, added support for 4096 × 2160 at 24 Hz, 3840 × 2160 at 24, 25, and 30 Hz, and 1920 × 1080 at 120 Hz. Compared to HDMI 1.3, 3 more features added which are HDMI Ethernet Channel (HEC) , audio return channel (ARC), 3D Over HDMI, a new Micro HDMI Connector, an expanded set of color spaces.

● **HDMI 2.0:** Released on September 4, 2013 increases the maximum bandwidth to 18.0 Gbit/s. Other features of HDMI 2.0 include up to 32 audio channels, up to 1536 kHz audio sample frequency, the HE-AAC and DRA audio standards, improved 3D capability, and additional CEC functions.

● **HDMI 2.0a:** Was released on April 8, 2015, and added support for High Dynamic Range (HDR) video with static metadata.

● **HDMI 2.0b:** Was released March, 2016, support for HDR Video transport and extends the static metadata signaling to include Hybrid Log-Gamma (HLG).

● **HDMI 2.1:** Released on November 28, 2017. It adds support for higher resolutions and higher refresh rates, Dynamic HDR including 4K 120 Hz and 8K 120 Hz.

● **DisplayPort:** A VESA standard interface primarily for video, but also for audio, USB and other data. DisplayPort (or DP) is backwards compatible with HDMI, DVI and VGA.

● **DP 1.1:** Was ratified on 2 April 2007, and version 1.1a was ratified on 11 January 2008. DisplayPort 1.1 allow a maximum bandwidth of 10.8 Gbit/s (8.64 Gbit/s data rate) over a standard 4-lane main link, enough to support 1920x1080@60Hz

● **DP 1.2:** Introduced on 7 January 2010, effective bandwidth to 17.28 Gbit/s support increased resolutions, higher refresh rates, and greater color depth, maximum resolution 3840 × 2160@60Hz

● **DP 1.4:** Publish on 1 Mar, 2016. overall transmission bandwidth 32.4 Gbit/s , DisplayPort 1.4 adds support for Display Stream Compression 1.2 (DSC), DSC is a "visually lossless" encoding technique with up to a 3:1 compression ratio. Using DSC with HBR3 transmission rates, DisplayPort 1.4 can support 8K UHD (7680 × 4320) at 60 Hz or 4K UHD (3840 × 2160) at 120 Hz with 30 bit/px RGB color and HDR. 4K at 60 Hz 30 bit/px RGB/HDR can be achieved without the need for DSC.

● **Multi-mode Fiber:** Fibers that support many propagation paths or transverse modes are called multi-mode fibers, generally have a wider core diameter and are used for short-distance communication links and for applications where high power must be transmitted.

● **Single-mode Fiber:** Fiber that support a single mode are called single-mode fibers. Single-mode fibers are used for most communication links longer than 1,000 meters (3,300 ft).

● **SFP:** Small form-factor pluggable , is a compact, hot-pluggable network interface module used for

both telecommunication and data communications applications.

● **Optical Fiber Connector:** Terminates the end of an optical fiber, and enables quicker connection and disconnection than splicing. The connectors mechanically couple and align the cores of fibers so light can pass. 4 most common types of optical fiber connectors are SC, FC, LC,ST.

● **SC:** (Subscriber Connector), also known as the square connector was also created by the Japanese company – Nippon Telegraph and Telephone. SC is a push-pull coupling type of connector and has a 2.5mm diameter. Nowadays, it is used mostly in single mode fiber optic patch cords, analog, GBIC, and CATV. SC is one of the most popular options, as its simplicity in design comes along with great durability and affordable prices.

● **LC :** (Lucent Connector) is a small factor connector (uses only a 1.25mm ferrule diameter) that has a snap coupling mechanism. Because of its small dimensions, it is the perfect fit for high-density connections, XFP, SFP, and SFP+ transceivers.

● **FC:** (Ferrule Connector) is a screw type connector with a 2.5mm ferrule. FC is a round shaped threaded fiber optic connector,mostly used on Datacom, telecom, measurement equipment, single-mode laser.

● **ST:** (Straight Tip) was invented by AT&T and uses a bayonet mount along with a long spring-loaded ferrule to support the fiber.











● **USB:** Universal Serial Bus is a standard that was developed in the mid-1990s that defines cables, connectors and communication protocols. This technology is designed to allow a connection, communication and power supply for peripheral devices and computers.

● **USB 1.1:** Full-Bandwidth USB, specification was the first release to be widely adopted by the consumer market. This specification allowed for a maximum bandwidth of 12Mbps.

● **USB 2.0:** or Hi-Speed USB, specification made many improvements over USB 1.1. The main improvement was an increase in bandwidth to a maximum of 480Mbps.

● **USB 3.2:** Super Speed USB with 3 varieties of 3.2 Gen 1(original name USB 3.0), 3.2Gen 2(original name USB 3.1), 3.2 Gen 2x2 (original name USB 3.2) with speed up to 5Gbps,10Gbps,20Gbps respectively.

USB version and connectors figure:

	Type A	Type B	Mini A	Mini B	Micro-A	Micro-B	Type C
USB 2.0							
USB 3.0							
USB 3.1&3.2							

● **NTSC:** The colour video standard used in North America and some other parts of the world created by the National Television Standards Committee in the 1950s. NTSC utilizes an interlaced video signals.

● **PAL:** Phase Alternate Line. A television standard in which the phase of the colour carrier is alternated from line to line. It takes four full images (8 fields) for the colour-to-horizontal images (8 fields) for the colour-to-horizontal phase relationship to return to the reference point. This alternation helps cancel out phase errors. For this reason, the hue control is not needed on a PAL TV set. PAL, is widely used in Western Europe, Australia, Africa, the Middle East, and Micronesia. PAL uses 625-line, 50-field (25 fps) composite colour transmission system.

● **SMPTE:** Society of Motion image and Television Engineers. A global organization, based in the United States, that sets standards for baseband visual communications. This includes film as well as video and television standards.

● **VESA:** Video Electronics Standards Association. An organization facilitating computer graphics through standards.

● **HDCP:** High-bandwidth Digital Content Protection (HDCP) was developed by Intel Corporation and is in wide use for protection of video during transmission between devices.

● **HDBaseT:** A video standard for the transmission of uncompressed video (HDMI signals) and related features using Cat 5e/Cat6 cabling infrastructure.

● **ST2110:** A SMPTE developed standard, ST2110 describes how to send digital video over IP networks. Video is transmitted uncompressed with audio and other data in a separate streams. SMPTE2110 is intended principally for broadcast production and distribution facilities where quality and flexibility are more important.

● **SDVoE:** Software Defined Video over Ethernet (SDVoE) is a method for transmission, distribution and management AV signals using a TCP/IP Ethernet infrastructure for transport with low latency. SDVoE is commonly used in integration applications.

● **Dante AV:** The Dante protocol was developed for and widely adopted in audio systems for the transmission of uncompressed digital audio on IP based networks. The more recent Dante AV specification includes support for digital video.

● **NDI:** Network Device interface (NDI) is a software standard developed by NewTek to enable video-compatible products to communicate, deliver, and receive broadcast quality video in a high quality, low latency manner that is frame-accurate and suitable for switching in a live production environment over TCP (UDP) Ethernet based networks. NDI is commonly found in broadcast applications.

● **RTMP:** Real-Time Messaging Protocol (RTMP) was initially a proprietary protocol developed by Macromedia (now Adobe) for streaming audio, video and data over the Internet, between a Flash player and a server.

● **RTSP:** The Real Time Streaming Protocol (RTSP) is a network control protocol designed for use in entertainment and communications systems to control streaming media servers. The protocol is used for establishing and controlling media sessions between end points.

● **MPEG:** Moving Picture Experts Group is a working group formed from ISO and IEC developing standards that allow audio/video digital compression and Transmission.

● **H.264:** Also known as AVC (Advanced Video Coding) or MPEG-4i is a common video compression standard. H.264 was standardized by the ITU-T Video Coding Experts Group (VCEG) together with the ISO/IEC JTC1 Moving Picture Experts Group (MPEG).

● **H.265:** Also known as **HEVC** (High Efficiency Video Coding) H.265 is the successor to the widely used H.264/AVC digital video coding standard. Developed under the auspices of ITU, resolutions up to 8192x4320 may be compressed.

● **API:** An Application Programming Interface (API) provides a predefined function which allows access capabilities and features or routines via a software or hardware, without accessing source code or understanding the details of inner working mechanism. An API call may execute a function and/or provide data feedback/report.

● **DMX512:** The communication standard developed by USITT for entertainment and digital lighting systems. The wide adoption of the Digital Multiplex (DMX) protocol has seen the protocol used for a wide range of other devices including video controllers. DMX512 is delivered over cable of 2 twisted pairs with 5pin XLR cables for connection.

● **ArtNet:** An ethernet protocol based on TCP/IP protocol stack, mainly used in entertainment/events applications. Built on the DMX512 data format, ArtNet enables multiple "universes" of DMX512 to be transmitted using ethernet networks for transport.

● **MIDI:** MIDI is the abbreviation of Musical Instrument Digital Interface. As the name indicates the protocol was developed for communication between electronic musical instruments and latterly computers. MIDI instructions are triggers or commands sent over twisted pair cables, typically using 5pin DIN connectors.

● **OSC:** The principle of Open Sound Control (OSC) protocol is for networking sound synthesizers, computers, and multimedia devices for musical performance or show control. As with XML and JSON, the OSC protocol allows sharing data. OSC is transported via UDP packets between devices connected on an Ethernet.

● **Brightness:** Usually refers to the amount or intensity of video light produced on a screen without regard to colour. Sometimes called black level.

● **Contrast Ratio:** The ratio of the high light output level divided by the low light output level. In theory, the contrast ratio of the television system should be at least 100:1, if not 300:1. In reality, there are several

limitations. Well-controlled viewing conditions should yield a practical contrast ratio of 30:1 to 50:1.

● **Colour Temperature:** The colour quality, expressed in degrees Kelvin (K), of a light source. The higher the colour temperature, the bluer the light. The lower the temperature, the redder the light. Benchmark colour temperature for the A/V industry include 5000°K, 6500°K, and 9000°K.

● **Saturation:** Chroma, Chroma gain. The intensity of the colour, or the extent to which a given colour in any image is free from white. The less white in a colour, the truer the colour or the greater its saturation. Saturation is the amount of pigment in a colour, and not the intensity.

● **Gamma:** The light output of a CRT is not linear with respect to the voltage input. The difference between what you should have and what is actually output is known as gamma.

● **Frame:** In interlaced video, a frame is one complete image. A video frame is made up of two fields, or two sets of interlaced lines. In a film, a frame is one still image of a series that makes up a motion image.

● **Genlock:** Allows synchronisation of otherwise video devices. A signal generator provides a signal pulses which connected devices can reference. Also see Black Burst and Color Burst.

● **Blackburst:** The video waveform without the video elements. It includes the vertical sync, horizontal sync, and the Chroma burst information. Blackburst is used to synchronize video equipment to align the video output.

● **Colour Burst:** In colour TV systems, a burst of subcarrier frequency located on the back part of the composite video signal. This serves as a colour synchronizing signal to establish a frequency and phase reference for the Chroma signal. Colour burst is 3.58 MHz for NTSC and 4.43 MHz for PAL.

● **Colour Bars:** A standard test pattern of several basic colours (white, yellow, cyan, green, magenta, red, blue, and black) as a reference for system alignment and testing. In NTSC video, the most commonly used colour bars are the SMPTE standard colour bars. In PAL video, the most commonly used colour bars are eight full field bars. On computer monitors the most commonly used colour bars are two rows of reversed colour bars

● **Seamless Switching:** A feature found on many video switchers. This feature causes the switcher to wait until the vertical interval to switch. This avoids a glitch (temporary scrambling) which often is seen when switching between sources.

● **Scaling:** A conversion of a video or computer graphic signal from a starting resolution to a new resolution. Scaling from one resolution to another is typically done to optimize the signal for input to an image processor, transmission path or to improve its quality when presented on a particular display.

● **PIP:** Picture-In-Picture. A small image within a larger image created by scaling down one of image to make it smaller. Other forms of PIP displays include Picture-By-Picture (PBP) and Picture- With-Picture (PWP), which are commonly used with 16:9 aspect display devices. PBP and PWP image formats require a separate scaler for each video window.

● **HDR:** is a high dynamic range (HDR) technique used in imaging and photography to reproduce a greater dynamic range of luminosity than what is possible with standard digital imaging or photographic techniques. The aim is to present a similar range of luminance to that experienced through the human visual system.

● **UHD:** Standing for Ultra High Definition and comprising 4K and 8K television standards with a 16:9 ratio, UHD follows the 2K HDTV standard. A UHD 4K display has a physical resolution of 3840x2160 which is four times the area and twice both the width and height of a HDTV/Full HD (1920x1080) video signal.

● **EDID:** Extended Display Identification Data. EDID is a data structure used to communicate video display information, including native resolution and vertical interval refresh rate requirements, to a source device. The source device will then output the provided EDID data, ensuring proper video image quality.

6.3 Revision History

The table below lists the changes to the User Manual.

Format	Time	ECO#	Description	Principal
V1.0	2021-07-19	0000#	Release	Sylvia
V1.1	2021-08-06	0001#	Update upgrade guide	Sylvia

All information herein is Xiamen RGBlink Science & Technology Co Ltd. excepting noted. **RGBlink** is a registered trademark of Xiamen RGBlink Science & Technology Co Ltd. While all efforts are made for accuracy at time of printing, we reserve the right to alter otherwise make change without notice.